
Portman 21 Washbasin 40cm 1 Taphole, Overflow, No Chainstay

S2157 Portman 21 washbasin 40cm, 1 taphole with overflow, no chainstay hole E0157 Wall fixing set A6697 Contour 21+ 1 hole thermostatic basin mixer, single sequential lever with copper tails S8722 Waste 1¼" brass strainer waste, 80mm slotted tail S8920 Trap 1¼" plastic resealing bottle, 75mm seal, multi-purpose outlet

OPTIONS

E0062	Basin fixing set for IPS panels or block walls		
B8263	Avon 21 1 hole washbasin mixer , self closing push button, variable temperature control with 15mm female connector flexible hoses on inlets. Flow regulated to 3.7 litres per minute maximum to comply with Water Technology List requirements.		
A6698	Contour 21+ 1 hole thermostatic basin mixer, single sequential lever with flexible tails		
A6790	Contour 21+ Outline 1 hole thermostatic basin mixer, single sequential lever with flexible tails		
S8733	Waste 1¼" brass anti theft swivel plug waste, 80mm slotted tail		
S8800	Waste 1½" plastic waste with bead chain and plug, 80mm slotted tail, bolt stay $$		
S8900	Trap 1½" metal bottle, 75mm seal, outlet screwed 1½" BSP male with compression nut and ring		
S9138	Bracket concealed with clamps and centre waste support for Portman 21, 40cm washbasins		



ILLUSTRATED PRODUCT DETAILS

Sizes		Finishes	
S2157	w:400 x d:365	S2157	White (01)
Weights	;		
S2157	9.70 KG	E0157	Neutral / No Finish (67)
E0157	0.16 KG		
A6697	2.10 KG	A6697	Chrome (AA)
S8722	0.22 KG		
S8920	2.00 KG	S8722	Chrome (AA)
Materials			
S2157	Vitreous China	S8920	Neutral / No Finish
E0157	Metal		(67)
A6697	Chrome Plated Brass	Capacity	
S8722	Chrome Plated Metal	S2157	3.3 litres
S8920	Plastic		3.5 35
		Flow rate	es
		A6697	3.9 Litres per minute @ 3 bar pressure
			•

Special Notes

S9138 Bracket for 40cm basins Recommended fixing heights (floor to front rim); Nursery use 600mm



Portman 21 Washbasin 40cm 1 Taphole, Overflow, No Chainstay

Infant use 700mm
Junior use 750mm
Senior/adult use 780-800mm.
Washbasin wall mounted using E015767 wall fixing set or panel mounted using E006267 fixing set

